

## LED LARGE BEACON



PART.NO.	PROGRAMMABLE FLASH PATTERN	COLOUR	CURRENT MAXIMUM DRAW @ 12V	OPERATING VOLTAGE	DIMENSIONS
L3000AB	Single 80 FPM	Amber	3.2 Amps	12-24 VDC	127mm (H) 161mm (D)
	Double 80 FPM				
L3000BB	Quad 72 FPM	Blue	3.2 Amps	12-24 VDC	127mm (H) 161mm (D)
	Rotating 165 FPM - 2 Panel				
L3000CB	Rotating 165 FPM - 4 Panel	Clear	3.2 Amps	12-24 VDC	127mm (H) 161mm (D)
	Rotating 165 FPM - 4 Panel				
L3000GB	The above 5 patterns flash in cycle (Auto)	Green	3.2 Amps	12-24 VDC	127mm (H) 161mm (D)
L3000RB		Red	3.2 Amps	12-24 VDC	127mm (H) 161mm (D)

- Selectable flash patterns.
- PC Board is epoxy potted to extend the lifespan of the beacon.
- Also available as a magnetic beacon.
- To ensure that moisture does not affect the operation of the beacon, always check that the O-ring is in the correct position.

## 3000 SERIES REPLACEMENT PARTS



MAGNETIC KIT	POLE MOUNT	AMBER LENS	BLUE LENS	CLEAR LENS	GREEN LENS	RED LENS
3000M-KIT	3000PM	3000AL	3000BL	3000CL	3000GL	3000RL

## TECHNICAL DRAWING

